

Nista Devices Technical Support:

 	<p>+41 55 5085814</p> <p>support@nistadevices.com</p>
<p>Documentation on all Nista Devices GmbH products can be found on the website - http://www.nistadevices.com/</p>	

1 How to configure IP394X for outgoing calls directly to destination IP address

1.1 Introduction

The IP-394X Nista IP Door Phones supports Peer-To-Peer (P2P)- direct to destination IP address outgoing calls and incoming calls from IP address remote SIP callers.

1.2 Direct outgoing call from IP-394X to destination IP Address

In case if IP39-4x unit's front panel accomplished with the Keypad, the direct IP call can be initiated to Day & Night and Speed Dial (SPD) destinations. In case of Single button front panel, the P2P call can be initiated to Day & Night destinations only.

To configure IP-394X for P2P calls to Day & Night destinations:

- Go to Telephony / Day and Night Settings or Telephony / Speed Dial screens in the IP-394X Management web interface
- Configure IP-394X call destination as example shown on the picture below, where 10.10.10.2 is the destination SIP client IP address. (*Note: The full destination SIP client address string is: **sip:XXX.XXX.XXX.XXX:NNNN**, where*

XXX.XXX.XXX.XXX – the destination SIP client IP address

NNNN – The SIP protocol signaling port number. In case of usage the SIP default signaling port number = 5060, it can be missed in the string

Day Time Destination	<input type="text" value="sip:10.10.10.2"/>
Night Time Destination	<input type="text" value="sip:10.10.10.2"/>
<input type="button" value="Save"/> <input type="button" value="Cancel"/>	

- Save configuration
- Press 'Ring' button on the IP-394X front panel
- IP-394X initiates call to SIP client destination

To configure IP-39-4X for P2P calls to Speed Dial destinations:

- Go to Telephony / Speed Dial screens in the IP-394X Management web interface
- Configure IP-304X call destination as example shown on the picture below, where 10.10.10.2 SIP client destination IP address.

Telephony->Speed Dial

Speed Dial No. 01 ▲ ▼

SPD	Day Time Destination	Night Time Destination	No Answer Forward Destination	Door 1 Opening Code	Door 2 Opening Code	Description
01	sip:10.10.10.2	sip:10.10.10.2		77	88	Ipad iPhone
02						

- Save configuration
- Select the required SPD by using arrow buttons and press 'Ring' or wait until IP-394X initiates a call
- IP-394X initiates direct IP call to destination